

WATHERPROOF BATTERIES

ACC ...

APPLICATION

Long-life lead-sealed rechargeable batteries. Withstand demanding operating conditions such as overloading and very low discharge. Do not require any maintenance.



Code	Power VA	Voltage V-	Rating A/h	Dimensions L x P x H mm.	Weight Kg	Data Sheet
ACC 019	25	12	2,3	178 x 34 x 65	0,9	-
ACC 060	77	12	7,0	151 x 64,5 x 97,5	2,5	-
ACC 150	180	12	17	181 x 76 x 167	6	-
ACC 240	260	12	24	175 x 166 x 125	8,1	-
ACC 400	480	12	40	197 x 165 x 170	14	-

METHOD OF CHOOSING POWER SUPPLY IN RELATION TO SYSTEM TO BE ENERGISED

- Calculate the total power absorbed P_t in VA by the system which has to be energised by adding together all the consumptions of the single components of the system: detectors P_r , sensors P_s (only SRS 158-258, SRC 358), valves P_v , external alarms P_a . Power consumption by sensors SGC ..., SGR ... must not be added since this is already included in that of the detectors which energise them..
 $P_t = P_r + P_s + P_v + P_a$. The power of the power unit must be greater than or equal to P_t .
- By multiplying the power absorbed, P_t , by the number of hours h for which it is necessary to keep the system running efficiently without mains supply, the power effectively necessary, P_e , is obtained.
 $P_e = P_t \times h$. The power of the battery must not be less than P_e . If a single battery is not sufficient, use two or more batteries in parallel.